

Regularization of chattering phenomena via bounded variation controls

Roberta Ghezzi, Marco Caponigro, Benedetto Piccoli, Emmanuel Trélat

► **To cite this version:**

Roberta Ghezzi, Marco Caponigro, Benedetto Piccoli, Emmanuel Trélat. Regularization of chattering phenomena via bounded variation controls. NETCO 2014, 2014, Tours, France. <hal-01024604>

HAL Id: hal-01024604

<https://hal.inria.fr/hal-01024604>

Submitted on 16 Jul 2014

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Regularization of chattering phenomena via bounded variation controls

Roberta Ghezzi

Institut de Mathématiques de Bourgogne
University of Burgundy

joint work with
M. Caponigro, B. Piccoli, E. Trélat

NetCo 2014
Tours, June 23rd 2014

Outline

- 1 Motivation
 - what is chattering?
 - how often does it occur?
- 2 Convergence results
 - convergence for the perturbed problem
 - rate of convergence and switching times
- 3 Open problems
 - rate of convergence for the perturbed problem
 - generic rate of convergence

Fuller's Problem [Fuller 1961]

Control System

$$\begin{cases} \dot{x}_1 = x_2, \\ \dot{x}_2 = u, \end{cases} \quad |u| \leq 1$$

Cost

$$\begin{aligned} &\text{Minimize} && \int_0^{t_f} x_1^2(s) ds \\ &x(0) = \bar{x} \\ &x(t_f) = 0 \end{aligned}$$


Fuller's Problem [Fuller 1961]

Control System

$$\begin{cases} \dot{x}_1 = x_2, \\ \dot{x}_2 = u, \end{cases} \quad |u| \leq 1$$

Cost

$$\begin{aligned} &\text{Minimize} && \int_0^{t_f} x_1^2(s) ds \\ &x(0) = \bar{x} \\ &x(t_f) = 0 \end{aligned}$$



- optimal controls are bang-bang with *infinitely many* switchings
- switchings take place on the curve $\{x_1 + C|x_2| = 0\}$, $C \sim 0.44$
- time intervals between consecutive switches decrease in a *geometric progression*

Examples of chattering

Control System

$$\dot{x} = f(x, u) \quad u \in \mathcal{U}$$

Cost

$$\begin{aligned} \text{Minimize} \quad & \int_0^{t_f} L(s, x, u) ds \\ & x(0) = \bar{x} \\ & x(t_f) = 0 \end{aligned}$$

Examples of chattering: state constraints

Control System


$$\dot{x} = f(x, u) \quad u \in \mathcal{U}$$

state constraints \implies

Cost

$$\begin{aligned} &\text{Minimize} && \int_0^{t_f} L(s, x, u) ds \\ &x(0) = \bar{x} \\ &x(t_f) = 0 \\ &h(x(s)) \leq 0 \end{aligned}$$

accumulation of contact points with the constraint's boundary



Examples of chattering

Control System


$$\dot{x} = f(x, u) \quad u \in \mathcal{U}$$

Cost

$$\begin{array}{l} \text{Minimize} \\ x(0) = \bar{x} \\ x(t_f) = 0 \end{array} \int_0^{t_f} L(s, x, u) ds$$

Examples of chattering: switching systems

switching systems



Cost

$$\text{Minimize} \int_0^{t_f} L(s, x, u) ds$$

$$x(0) = \bar{x}$$

$$x(t_f) = 0$$

accumulation of switchings between different locations

Occurring of chattering

Optimal control problem

$$\dot{x} = f_0(x) + u f_1(x) \quad u \in \mathcal{U} \quad \text{Minimize} \quad \int_0^{t_f} L_0(x) + u L_1(x) ds$$

$$x(0) = \bar{x} \quad x(t_f) = 0$$

- $f_0, f_1 \in \mathcal{C}^\infty(\mathbb{R}^n; \mathbb{R}^n)$
- $\mathcal{U} = \{v(\cdot) \text{ measurable } v(t) \in [-1, 1]\}$
- $L_0, L_1 \in \mathcal{C}^\infty(\mathbb{R}^n)$

Ubiquity of Fuller's phenomenon [Kupka 1990]

In sufficiently high state dimension, for single-input control affine problems with control affine cost solutions are *generically* chattering.

Regularization method

OCP

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

OCP_ε

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds + \varepsilon TV(u) \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

$$- \varepsilon > 0$$

$$- TV(u) = \sup \sum_{i=1}^n |u(t_{i+1}) - u(t_i)|$$

- problem OCP_ε admits a solution u_ε which is “regular” ($TV(u_\varepsilon) < \infty$)
- convergence $\int L(s, x_\varepsilon, u_\varepsilon) \rightarrow \int L(s, x^*, u^*)$ as $\varepsilon \rightarrow 0$, where u^* is a chattering solution of OCP

Regularization method

OCP

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

OCP_ε

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds + \varepsilon TV(u) \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

- $\varepsilon > 0$
- $TV(u) = \sup \sum_{i=1}^n |u(t_{i+1}) - u(t_i)|$

- problem OCP_ε admits a solution u_ε which is “regular” ($TV(u_\varepsilon) < \infty$)
- convergence $\int L(s, x_\varepsilon, u_\varepsilon) \rightarrow \int L(s, x^*, u^*)$ as $\varepsilon \rightarrow 0$, where u^* is a chattering solution of OCP

Regularization method

OCP

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

OCP_ε

$$\left\{ \begin{array}{l} \text{Minimize } \int L(s, x, u) ds + \varepsilon TV(u) \\ x(0) = \bar{x} \\ x(t_f) = 0 \\ \dot{x} = f(x, u), \quad u \in \mathcal{U} \end{array} \right.$$

$$- \varepsilon > 0$$

$$- TV(u) = \sup \sum_{i=1}^n |u(t_{i+1}) - u(t_i)|$$

- problem OCP_ε admits a solution u_ε which is “regular” ($TV(u_\varepsilon) < \infty$)
- convergence $\int L(s, x_\varepsilon, u_\varepsilon) \rightarrow \int L(s, x^*, u^*)$ as $\varepsilon \rightarrow 0$, where u^* is a chattering solution of OCP

General setting and assumptions I

Optimal control problem

$$\dot{x} = f(x, u), \quad u \in \mathcal{U}$$

$$\text{Minimize}_{\substack{x(0) = \bar{x} \\ x(t_f) = 0}} \int_0^{t_f} L(s, x(s), u(s)) ds$$

where

- $f \in C^\infty(\mathbb{R}^n \times \mathbb{R}^m; \mathbb{R}^n)$, $f(0, 0) = 0$
- $\mathcal{U} = \{u(\cdot) \text{ measurable}, u(t) \in \mathbf{U}\}$, for a given subset $\mathbf{U} \subset \mathbb{R}^m$, $0 \in \overset{\circ}{\mathbf{U}}$
- $L \in C(\mathbb{R} \times \mathbb{R}^n \times \mathbb{R}^m)$

General setting and assumptions II

Assumptions

Controllability

1. $\text{Lie}_0\{f(u, \cdot) \mid u \in \mathbf{U}\} = \mathbb{R}^n$
2. 0 is small time locally controllable

Weak convexity

3. for every $(t, x) \in \mathbb{R} \times \mathbb{R}^n$ the set

$$\{(f(x, u), L(t, x, u) + \gamma) \mid u \in \mathbf{U}, \gamma \geq 0\} \text{ is convex}$$

Compactness

4. \mathbf{U} is compact
5. trajectories associated with admissible controls are uniformly bounded

Convergence

Theorem

Assume conditions 1-5 and assume that OCP has a solution (u^*, x^*) . Then, for every $\varepsilon > 0$, OCP_ε has a solution $(u_\varepsilon, x_\varepsilon)$ and

$$\lim_{\varepsilon \rightarrow 0} \int_0^{t_\varepsilon} L(s, x_\varepsilon(s), u_\varepsilon(s)) ds = \int_0^{t^*} L(s, x^*(s), u^*(s)) ds.$$

Moreover,

- $t_\varepsilon \rightarrow t^*$,
- $x_\varepsilon \rightarrow x^*$ uniformly.

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow[w^* - L^\infty]{} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \begin{array}{l} w \text{ is optimal for OCP,} \\ \text{i.e., } \int L(s, x^*, u^*) = \int L(s, x_w, w) \end{array}$$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \begin{array}{l} \text{convergence} \\ \int L(s, x_\varepsilon, u_\varepsilon) \text{ to } \int L(s, x^*, u^*) \end{array}$$

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow{w^* - L^\infty} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow w \text{ is optimal for OCP,}$$

i.e., $\int L(s, x^*, u^*) = \int L(s, x_w, w)$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \text{convergence}$$

$\int L(s, x_\varepsilon, u_\varepsilon)$ to $\int L(s, x^*, u^*)$

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow{w^* \rightarrow L^\infty} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow w \text{ is optimal for OCP,}$$

i.e., $\int L(s, x^*, u^*) = \int L(s, x_w, w)$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \text{convergence}$$

$\int L(s, x_\varepsilon, u_\varepsilon)$ to $\int L(s, x^*, u^*)$

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow{w^* - L^\infty} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow w \text{ is optimal for OCP,}$$

i.e., $\int L(s, x^*, u^*) = \int L(s, x_w, w)$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \text{convergence}$$

$\int L(s, x_\varepsilon, u_\varepsilon)$ to $\int L(s, x^*, u^*)$

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow[w^* - L^\infty]{} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \begin{array}{l} w \text{ is optimal for OCP,} \\ \text{i.e., } \int L(s, x^*, u^*) = \int L(s, x_w, w) \end{array}$$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \text{convergence}$$

$$\int L(s, x_\varepsilon, u_\varepsilon) \text{ to } \int L(s, x^*, u^*)$$

Idea of the proof

Step 1.

controllability
 compactness of $\{u \in \mathcal{U} \mid TV(u) \leq 1\}$
 lower s.c. of $TV(\cdot)$

$$\left. \vphantom{\begin{array}{l} \text{controllability} \\ \text{compactness of } \{u \in \mathcal{U} \mid TV(u) \leq 1\} \\ \text{lower s.c. of } TV(\cdot) \end{array}} \right\} \Rightarrow \text{existence for OCP}_\varepsilon$$

Step 2.

convexity
 compactness

$$\left. \vphantom{\begin{array}{l} \text{convexity} \\ \text{compactness} \end{array}} \right\} \Rightarrow \text{existence of } w \in \mathcal{U} \text{ and } \gamma \in L^1, \gamma \geq 0 \text{ such that}$$

$$(f(x_\varepsilon, u_\varepsilon), L(\cdot, x_\varepsilon, u_\varepsilon)) \xrightarrow{w^* - L^\infty} (f(x_w, w), L(\cdot, x_w, w) + \gamma)$$

Step 3.

u_ε is optimal for OCP_ε
 density of bv controls

$$\left. \vphantom{\begin{array}{l} u_\varepsilon \text{ is optimal for } \text{OCP}_\varepsilon \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \begin{array}{l} w \text{ is optimal for OCP,} \\ \text{i.e., } \int L(s, x^*, u^*) = \int L(s, x_w, w) \end{array}$$

Step 4.

w is optimal for OCP
 density of bv controls

$$\left. \vphantom{\begin{array}{l} w \text{ is optimal for OCP} \\ \text{density of bv controls} \end{array}} \right\} \Rightarrow \text{convergence}$$

$$\int L(s, x_\varepsilon, u_\varepsilon) \text{ to } \int L(s, x^*, u^*)$$

Rate of convergence

Proposition

Assume that

- conditions 1, 2 (controllability), and 4,5 (compactness) are satisfied;
- OCP has a solution (u^*, x^*) and there exists $t_n \uparrow T^*$ such that $TV(u^*|_{[0, t_n]}) < \infty$;
- the time-optimal map is $C^{0, \alpha}$ for some $\alpha \in (0, 1]$ on a neighborhood of 0.

Then there exist a sequence $v_n : [0, T_n] \rightarrow \mathbf{U}$ of admissible controls such that

- $TV(v_n) < \infty$,
- $v_n \rightarrow u^*$ strongly in L^1 , and

$$\int_0^{T_n} L(t, x_n, v_n) dt - \int_0^{T^*} L(t, x^*, u^*) dt \leq C(T^* - t_n)^\alpha.$$

Remarks

Theorem	Proposition
<ul style="list-style-type: none">▶ general setting▶ computable controls u_ε▶ convergence only	<ul style="list-style-type: none">▶ general setting▶ controls v_n given by truncations of u^*▶ convergence + rate in terms of switching times

[Zelikin 1999] - [Manita 1996]

- specific OCP (small perturbation of Fuller's dynamics in higher dimension with Fuller's cost)
- controls v_n given by truncations of u^*
- convergence + rate in terms of switching times (exponential in this case)

Remarks

Theorem	Proposition
<ul style="list-style-type: none">▶ general setting▶ computable controls u_ε▶ convergence only	<ul style="list-style-type: none">▶ general setting▶ controls v_n given by truncations of u^*▶ convergence + rate in terms of switching times


[Zelikin 1999] - [Manita 1996]

- specific OCP (small perturbation of Fuller's dynamics in higher dimension with Fuller's cost)
- controls v_n given by truncations of u^*
- convergence + rate in terms of switching times (exponential in this case)

Open problems I

1. Rate of convergence for the regularized problem OCP_ε

\Rightarrow uniform small time normal reachability property



Controllability assumptions \Rightarrow

- w_y is piecewise constant with **at most q switchings**,
- the time τ_y to steer y to 0 satisfies **$\tau_y \leq C|y|$** ,

where **q, C do not depend on y** ?

Open problems II

2. Generic rate of convergence

- Fuller's problem: switching times converge *geometrically*
- Kupka 1990 \Rightarrow exponential rate of convergence is "stable"

Can we expect lower rates of convergence? What rates are stable?