

Averaging for minimum time control problems and applications

Jérémy Rouot, Jean-Baptiste Caillau, Jean-Baptiste Pomet

▶ **To cite this version:**

Jérémy Rouot, Jean-Baptiste Caillau, Jean-Baptiste Pomet. Averaging for minimum time control problems and applications. 18th French - German - Italian Conference on Optimization, Sep 2017, Paderborn, Germany. hal-02483225

HAL Id: hal-02483225
https://inria.hal.science/hal-02483225

Submitted on 18 Feb 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Averaging for minimum time control problems and applications

18th French - German - Italian Conference on Optimization

Paderborn, September 25 - 28, 2017

Jérémy Rouot

Joint work with J.-B. Caillau and J.-B. Pomet
from INRIA Sophia Antipolis, France.

Coordinates (I, φ)

- $I \in U(\subset \mathbb{R}^5)$: geometric elements of the ellipse,
- $\varphi \in S^1$: position on the orbit.

Equations of motion In first approximation,

$$\dot{I} = 0, \quad \dot{\varphi} = \omega(I) > 0$$

I is a slow variable compared to φ.

$$\min_{t_f,\,|u|\le 1} \quad t_f$$


$$\text{s.t.} \qquad \dot{I} = \varepsilon F_0(I,\varphi,\varepsilon) + \varepsilon \sum_{i=1}^{3} u_i F_i(I,\varphi,\varepsilon), \qquad I(0) = I_0$$

$$\dot{\varphi} = \omega(I) + \varepsilon G_0(I,\varphi,\varepsilon) + \varepsilon \sum_{i=1}^{3} u_i G_i(I,\varphi,\varepsilon), \quad I(t_f) = I_f.$$

$0 < \varepsilon \ll 1$, and I_0, I_f are given. $\varphi(0)$ and $\varphi(t_f)$ are free.
$F_i(\cdot,\varphi,\cdot), G_i(\cdot,\varphi,\cdot)$ $i = 0 \dots 3$ are **2π-periodic** w.r.t. φ, $u \in \mathbb{R}^3$.

F_0, G_0 modeled perturbations

- high order terms in the gravitational potential of the Earth,
- luni-solar perturbation, ...



Let $f(X,\psi,\varepsilon), g(X,\psi,\varepsilon)$ be two vector fields **2π-periodic** w.r.t. $\psi \in S^1$.

Unperturbed system $\quad \dot{X} = 0, \quad \dot{\psi} = \omega(X)$

Perturbed system

$$\dot{X} = \varepsilon f(X,\psi,\varepsilon), \quad \dot{\psi} = \omega(X) + \varepsilon g(X,\psi,\varepsilon)$$

where $X \in C \subset \mathbb{R}^n$.There are $C' \subset C$ and $\tau > 0$ s.t.

$$Y' = \overline{f}(Y), \quad \overline{f}(X) = \frac{1}{2\pi}\int_0^{2\pi} f(X,\psi,\varepsilon=0)\,\mathrm{d}\psi,$$

have a well-defined solution defined on $[0,\tau]$ for every initial condition $Y(0) \in C'$.

Theorem 1. $\exists \varepsilon_0 > 0$, $0 < \varepsilon < \varepsilon_0$ *and for every initial condition in* $C' \times S^1$, *the perturbed system has a solution on* $[0,\tau/\varepsilon]$ *s.t.*

$$|X(t) - Y(\varepsilon t)| = O(\varepsilon)$$

PMP: a minimizing trajectory is projection of an extremal $(I(.), \varphi(.), p_I(.), p_\varphi(.))$ solution of the Hamiltonian system

$$H(I, \varphi, p_I, p_\varphi, \varepsilon) = p_\varphi \omega(I) + \varepsilon K_0(I, \varphi, p_I, p_\varphi, \varepsilon),$$

$$K_0 := H_0 + \sqrt{\sum_{i=1}^{3} H_i^2}, \ H_i(I, \varphi, p_I, p_\varphi, \varepsilon) = p_I F_i(I, \varphi, \varepsilon) + p_\varphi G_i(I, \varphi, \varepsilon), \ i = 0, ..., 3.$$

Extremal system

$$\dot{I} = \varepsilon \frac{\partial K_0}{\partial p_I}, \quad \dot{p_I} = -p_\varphi \omega' - \varepsilon \frac{\partial K_0}{\partial I}$$

$$\dot{\varphi} = \omega + \varepsilon \frac{\partial K_0}{\partial p_\varphi}, \quad \dot{p_\varphi} = -\varepsilon \frac{\partial K_0}{\partial \varphi}$$

Theorem 2. *Normalizing on* $\boldsymbol{H = \varepsilon}$ *(normal extremals), we have*

$$p_\varphi = -\varepsilon h(I, \varphi, p_I, \varepsilon)$$

$$0 = \frac{\partial}{\partial p_I}\left(H(I,\varphi,p_I,-\varepsilon h(I,\varphi,p_I,\varepsilon),\varepsilon) - \varepsilon \right) = \varepsilon \frac{\partial K_0}{\partial p_I} - \varepsilon \frac{\partial h}{\partial p_I}\frac{\partial H}{\partial p_\varphi}$$

$\Rightarrow \dot{I} = \varepsilon \dfrac{\partial h}{\partial p_I}\dot{\varphi}$, and similarly, we have: $\dot{p}_I = -\varepsilon \dfrac{\partial h}{\partial I}\dot{\varphi}$.

$\Rightarrow$ Reparametrization w.r.t.: $s = \varepsilon(\varphi - \varphi_0)$.

Definition 3. *The* **average** *boundary value problem is*

$$\frac{\mathrm{d}\overline{I}}{\mathrm{d}s} = \frac{\partial \overline{h}}{\partial p_I}, \qquad \frac{\mathrm{d}\overline{p}_I}{\mathrm{d}s} = -\frac{\partial \overline{h}}{\partial I}$$
$$\overline{I}(0) = I_0, \quad \overline{I}(\overline{s}_f) = I_f, \quad \overline{h} = 0$$

where

$$\overline{h}(I,p_I) := \frac{1}{2\pi}\int_0^{2\pi} h(I,\varphi,p_I,\varepsilon{=}0)\mathrm{d}\varphi = \frac{1}{2\pi}\int_0^{2\pi} \frac{K_0 - 1}{\omega}(I,\varphi,p_I,p_\varphi{=}0,\varepsilon{=}0)\mathrm{d}\varphi.$$

Let

$$\overline{S}(s_f, p_0) = (\overline{I}(s_f, p_0) - I_f, \overline{h}(I_0, p_0))$$

be the shooting function associated with the average dynamic

$$\frac{\mathrm{d}\overline{z}}{\mathrm{d}s} = \overrightarrow{\overline{h}}(\overline{z}(s)), \quad \overline{z} = (\overline{I}, \overline{p}_I)$$

Remark 4. *$\overline{h}$ is smooth outside $\overline{\Sigma}$ where*

$$\Sigma = \{(I, p_I, \varphi) \in T^*M \times S^1 \mid p_I \cdot F_i(I, \varphi, p_I, \varepsilon) = 0,\ i = 1, 2, 3\}$$

in

$$\overline{\Sigma} = \Pi(\Sigma), \quad \Pi : T^*M \times S^1 \to T^*M.$$

For $\varepsilon > 0$, consider

$$S_\varepsilon(s_f, p_0) = (I(s_f, p_0) - I_f, \overline{h}(I_0, p_0))$$

be the shooting function associated with the non-average dynamic

$$\frac{\mathrm{d}z}{\mathrm{d}s} = \overrightarrow{h}(s/\varepsilon, z(s), \varepsilon), \quad z = (I, p_I).$$

Remark 5. *Note that solutions of $S_\varepsilon(s_f, p_0) = 0$ doesn't define strict extremals in the sense that the true conditions*

$$h(\varphi_0, z_0, \varepsilon) = h(\varphi_f, z_f, \varepsilon) = 0$$

are replace by

$$\overline{h}(z_0) = 0.$$

They are called "quasi-extremals".

Theorem 6. *Let $(I^\varepsilon(.))_\varepsilon$ be a family of non average trajectories (with "quasi-extremals" lifts) converging as $\varepsilon \to 0$ with fixed extremities I_0, I_f. Then the limit is solution of the average boundary value problem.*

Theorem 7. *Let $\overline{I}(.)$ be a trajectory of the average system which doesn't have conjugate points.*
Then, there exists a family of non average trajectories $(I^\varepsilon(.))_\varepsilon$ converging to $\overline{I}(.)$ as $\varepsilon \to 0$ satisfying the boundary values: $I^\varepsilon(0) = I_0$ and $I^\varepsilon(t_f) = I_f + O(\varepsilon)$ and under further assumptions, there exists (φ_0, p_0) s.t.

$$h(\varphi_0, z(0), \varepsilon) = 0 \quad \text{and} \quad h(s_f/\varepsilon + \varphi_0, z(s_f), \varepsilon) = 0.$$

Remark 8. *Numerical use: The solution of the average system can be used to* **initialize** *the shooting function of the non average system.*

Lemma 9. *Let $f : \mathbb{R}^n \to \mathbb{R}^n$ be a continuously differentiable function with a regular zero at $x = 0$, and let $f_\varepsilon : \mathbb{R}^n \to \mathbb{R}^n$, $\varepsilon > 0$, be continuous functions converging uniformly towards f on a neighborhood of the origin when $\varepsilon \to 0$.*
There exists $\varepsilon_0 > 0$ and $x : [0, \varepsilon_0] \to \mathbb{R}^n$ continuous at $\varepsilon = 0$, s.t. $x(0) = 0$ and

$$f_\varepsilon(x(\varepsilon)) = 0, \qquad \varepsilon \in (0, \varepsilon_0].$$

Proof of the convergence Theorem 7. Let $(\overline{s}_f, \overline{p}_0)$ the solution of the average system $(\overline{S}(\overline{s}_f, \overline{p}_0) = 0)$.

1. Apply Lemma 9 with $f = \overline{S}$ and $f_\varepsilon = S_\varepsilon$. Then there exists $p_0(\varepsilon) \to \overline{p}_0$ s.t. $\overline{h}(I_0, p_0(\varepsilon)) = 0$.

2. Assume

$$\exists \overline{\varphi}_0 \in S^1, \quad h(\overline{\varphi}_0, \overline{z}_0, \varepsilon = 0) = 0, \quad \frac{\partial h}{\partial \varphi}(\overline{\varphi}_0, \overline{z}_0, \varepsilon = 0) \neq 0, \quad (\overline{z}_0 = (I_0, \overline{p}_0)),$$

we construct $\varphi_0(p, \varepsilon)$ and we apply again Lemma 9 with $S_\varepsilon(\varphi_0, s_f, p_0)$ associated to

$$\frac{\mathrm{d}z}{\mathrm{d}s} = \overrightarrow{h}(s/\varepsilon + \boldsymbol{\varphi_0}, z(s), \varepsilon)$$

to satisfy the condition $\boldsymbol{h(\varphi_0, z(0), \varepsilon) = 0}$ for the non average extremals.

3. Assume


$$\exists \overline{\varphi}_f \in S^1, \quad h(\overline{\varphi}_f, \overline{z}_f, \varepsilon = 0) = 0, \quad \frac{\partial h}{\partial \varphi}(\overline{\varphi}_f, \overline{z}_f, \varepsilon = 0) \neq 0, \quad (\overline{z}_f = \overline{z}(\overline{s}_f, p_0)),$$

we construct $\varphi_f(\varepsilon)$ (Brouwer fix point theorem) and consider

$$\widetilde{s}_f(\varepsilon) = s_f(\varepsilon) + \varepsilon\varphi_f(\varepsilon),$$

so that

$$h(\widetilde{s}_f/\varepsilon + \varphi_0, z(\widetilde{s}_f), \varepsilon) = 0 \text{ and } I(\widetilde{s}_f) = I_f + O(\varepsilon).$$



(red) Some average orbits of the average system.
(blue) Non average trajectory in Cartesian coordinates.


Finsler norm $\mathcal{F} : TM \to \mathbf{R}$ smooth on $TM \backslash 0$ s.t.

- $\mathcal{F}(x, \lambda v) = \lambda \mathcal{F}(x, v)$, $\lambda > 0$
- $\partial^2 \mathcal{F}^2(x, v)/\partial v^2 > 0$


Finsler co-norm $F^* : T^*M \to \mathbf{R}$ smooth on $T^*M \backslash 0$ s.t.

- $F^*(x, \lambda p) = \lambda F^*(x, p)$, $\lambda > 0$,
- $\partial^2 (F^*)^2(x, p)/\partial p^2 > 0$

Theorem 10. *If* $\operatorname{rang} \{\partial^j F_i(I, \varphi, \varepsilon = 0)/\partial \varphi^j,\ i = 1, \ldots, 3,\ j \geq 0\} = 6$, *then* $\overline{K}_0$ *defined a symmetric Finsler co-norm.*



$\mathcal{F}_0$ Symmetric Finsler norm



$\mathcal{F}$ Non-symmetric Finsler norm

Earth oblateness perturbation

$$\begin{aligned} H &= p_\varphi \omega(I) + \varepsilon_{J_2} H_0(I, p_I, \varphi) + \varepsilon_{th} K_0(I, p_I, \varphi, p_\varphi, \varepsilon) \\ &= p_\varphi \omega(I) + \varepsilon \Big[\underbrace{\lambda H_0(I, p_I, \varphi) + (1-\lambda) K_0(I, p_I, \varphi, p_\varphi, \varepsilon)}_{K^\lambda(I, p_I, \varphi, p_\varphi, \varepsilon)} \Big] \\ &= p_\varphi \omega(I) + \varepsilon \end{aligned}$$

where $\varepsilon = \varepsilon_{J2} + \varepsilon_{th},\ \lambda = \varepsilon_{J2}/\varepsilon$.

We denote by $\overline{K}^\lambda$ the average of K^λ w.r.t. φ.

• *Q :* Is $(I, p_I) \mapsto \overline{K}^{\lambda}(I, p_I) = \lambda \overline{H}_0(I, p_i) + (1-\lambda)\overline{K}_0(I, p_I)$ a Finsler co-norm ?

Lemma 11. *For $I \in M$ fixed, consider the (unique) one-form $\overline{F}_0^{\star,\lambda}(I)$ solution of*

$$\overline{F_0}^{\star,\lambda}(I) = \underset{p \in \mathbb{R}^n}{\textit{argmin}} \left[1/2\,(1-\lambda)^2 \overline{K}_0(I,p)^2 - \lambda \langle p, \overline{F}_0(I) \rangle \right].$$

Proposition 12. *Let $I \in M$ fixed and λ_c s.t. $\overline{K}_0^{\lambda_c}(I, \overline{F_0}^{\lambda_c \star}(I)) = 1$. For all $\lambda < \lambda_c$,*

$$T_I^\star M \ni p \mapsto \overline{K}^{\lambda}(I,p) \in \mathbb{R}^+$$

is a Finsler co-norm (non-symmetric).


Proposition 13. *λ_c can be computed as*

$$\lambda_c(I) = \frac{1}{\overline{K}_0(I, p^\star) + 1},$$

where $p^\star = \langle \pi^\star, \overline{F}_0(I) \rangle \, \pi^\star$, $\pi^\star = \underset{\pi | \overline{K}_0(I,\pi)=1}{\textit{argmax}} \langle \pi, \overline{F}_0(I) \rangle$

Let I_f be a fixed extremity.
We construct I_0 by integrating the uncontrolled flow on $[0, \tau_d]$.


Uncontrolled dynamic during τ_d




Boundary value problems

	Average BVP	Non average BVP
Extremal system	$\overline{K}^\lambda$	$H/\varepsilon = K^\lambda + p_\varphi \omega(I,\varphi)/\varepsilon$
Free parameters	$\lambda,\ \tau_d$	$\lambda,\ \tau_d,\ \varepsilon$
Boundary values	$I(0) = I_0, I(\tau_f) = I_f$	$I(0) = I_0, I(t_f) = I_f$
	$\overline{K}^\lambda = 1$	$p_\varphi(0) = 0, p_\varphi(t_f) = 0, H = \varepsilon$


Settings We take ε small and analyze the dependance on λ when $\tau_d \to 0$ for both systems.



Curves $\lambda \mapsto \tau_f(\lambda)$ where $\tau_d \in \{$1e-2,1e-3,1e-4,1e-5$\}$ for the average system.



Minimum time w.r.t. to λ for the average system and its derivative w.r.t. λ.



Curves $\lambda \to \tau_f$ for the average and non average system where $\varepsilon = 10^{-3}$ et $\tau_d \in \{$1e-4,1e-5$\}$.

- relate the metric property to controllabilty property
- continuity of the value function at the critical value λ_c.
- averaging with several angles (and other perturbations): resonances